

TYPE: _____ QUANTITY: _____ PROJECT: _____

CATALOG NUMBER:

FIXTURE CCT WATTAGE VOLTAGE FINISH OPTION OPTION OPTION



- 1- 5" Diameter (127) canopy with universal mounting plate.
- 2- 36"Lg (914) silver braided power cable with aircraft safety cable.
- 3- Extruded aluminum driver housing.
- 4- **PR1691Q:** Diffused acrylic prismatic refractor.
PR1696Q: Aluminum reflector.
Inner surface: multi-faceted specular anodized.
Exterior surface: Satin anodized natural aluminum.

PR1691Q



PR1696Q



MATERIALS

Prisma is made of an extruded aluminum housing designed to optimize the functionality of the driver and solid state components.

Prisma is available with a choice of two interchangeable reflectors.

- Aluminum reflector designed to optimize light source performance and uniformity.
- Diffused acrylic prismatic refractor with a linear peripheral pattern providing general upward illumination with efficient down lighting.

ELECTRICAL

LED

DRIVER Standard driver is 0-10V dimming-ready (dims to 1%)* with: 120-277 multi-volt compatibility (50-60Hz), operating temperature range of -20°C/-4°F to +50°C/122°F, output over voltage protection, output over current protection and output short circuit protection with auto-recovery.

LED 3500K CCT/80 CRI or 4000K CCT/80 CRI.

LIFE

125,000hrs L₇₀B₅₀ (calculated projection from LM-80 data).

FINISH

Polyester powder coating is applied through an electrostatic process and oven cured for long term finish.

*L1L100 dims to 5%

MOUNTING

Maximum weight: 15.3lbs (6.9kg)

Mounts on a standard 4" (102) octagonal electrical box with 3 1/2" (89) C/C mounting holes.

CERTIFICATION

Tested to UL1598 and CSA 22.2 #250. ETL listed damp location.


Photometric testing per LM79-2008, LED Light source with LM80 certified testing. CE certification on request.

Rated IP20.



PR1691Q/PR1696Q SERIES PRISMA 16" - LED


TYPICAL PHOTOMETRY SUMMARY



PR1691Q-L1L100

Descriptive Information

Total delivered lumens: 11295 Lumens
 Input watts at 120V: 108.4 W
 Efficacy: 104 Lumens/Watt
 Source: LED
 CCT/CRI: 4000K/80CRI
 Maximum Candela = 10,836 @ 0°H/0°V





PR1696Q-L1L100

Descriptive Information

Total delivered lumens: 11149 Lumens
 Input watts at 120V: 108.4 W
 Efficacy: 103 Lumens/Watt
 Source: LED
 CCT/CRI: 4000K/80CRI
 Maximum Candela = 10,697 @ 0°H/0°V

Please visit our web site www.luminis.com for complete I.E.S. formatted download data.

LUMINAIRE SELECTION

MODEL#	LED LIGHT SELECTION	VOLTAGE ¹	FINISH												
 <input type="checkbox"/> PR1691Q	<table border="1"> <thead> <tr> <th>SUFFIX</th> <th>INPUT WATTS</th> <th>DELIVERED LUMENS</th> <th>CRI</th> </tr> </thead> <tbody> <tr> <td><input type="checkbox"/> L1L80</td> <td>74W</td> <td>8071</td> <td>80</td> </tr> <tr> <td><input type="checkbox"/> L1L100</td> <td>108W</td> <td>11295</td> <td>80</td> </tr> </tbody> </table>	SUFFIX	INPUT WATTS	DELIVERED LUMENS	CRI	<input type="checkbox"/> L1L80	74W	8071	80	<input type="checkbox"/> L1L100	108W	11295	80	<input type="checkbox"/> 120V <input type="checkbox"/> 208V <input type="checkbox"/> 240V <input type="checkbox"/> 277V	STANDARD COLORS <input type="checkbox"/> WHT Snow white <input type="checkbox"/> BKT Jet black <input type="checkbox"/> BZT Bronze <input type="checkbox"/> MST Matte silver
	SUFFIX	INPUT WATTS	DELIVERED LUMENS	CRI											
<input type="checkbox"/> L1L80	74W	8071	80												
<input type="checkbox"/> L1L100	108W	11295	80												
<table border="1"> <thead> <tr> <th>SUFFIX</th> <th>INPUT WATTS</th> <th>DELIVERED LUMENS</th> <th>CRI</th> </tr> </thead> <tbody> <tr> <td><input type="checkbox"/> L1L80</td> <td>74W</td> <td>7967</td> <td>80</td> </tr> <tr> <td><input type="checkbox"/> L1L100</td> <td>108W</td> <td>11149</td> <td>80</td> </tr> </tbody> </table>	SUFFIX	INPUT WATTS	DELIVERED LUMENS	CRI	<input type="checkbox"/> L1L80	74W	7967	80	<input type="checkbox"/> L1L100	108W	11149	80			
SUFFIX	INPUT WATTS	DELIVERED LUMENS	CRI												
<input type="checkbox"/> L1L80	74W	7967	80												
<input type="checkbox"/> L1L100	108W	11149	80												
 <input type="checkbox"/> PR1696Q	<table border="1"> <thead> <tr> <th>SUFFIX</th> <th>INPUT WATTS</th> <th>DELIVERED LUMENS</th> <th>CRI</th> </tr> </thead> <tbody> <tr> <td><input type="checkbox"/> L1L80</td> <td>74W</td> <td>7967</td> <td>80</td> </tr> <tr> <td><input type="checkbox"/> L1L100</td> <td>108W</td> <td>11149</td> <td>80</td> </tr> </tbody> </table>	SUFFIX	INPUT WATTS	DELIVERED LUMENS	CRI	<input type="checkbox"/> L1L80	74W	7967	80	<input type="checkbox"/> L1L100	108W	11149	80	<input type="checkbox"/> 120V <input type="checkbox"/> 208V <input type="checkbox"/> 240V <input type="checkbox"/> 277V	STANDARD COLORS <input type="checkbox"/> WHT Snow white <input type="checkbox"/> BKT Jet black <input type="checkbox"/> BZT Bronze <input type="checkbox"/> MST Matte silver
SUFFIX	INPUT WATTS	DELIVERED LUMENS	CRI												
<input type="checkbox"/> L1L80	74W	7967	80												
<input type="checkbox"/> L1L100	108W	11149	80												

OPTIONS

ELECTRICAL

- K35 3500K CCT 80 CRI (Multiplier 0.98)
- K4 4000K CCT 80 CRI

NOTE: Other CCT & higher CRI available, please consult factory.

NOTES

- 1- Luminaires are factory prewired for 120V unless otherwise specified.

